

AMENDMENTS TO THE CLAIMS

1. (Currently Amended) A digital camera comprising:

a diaphragm, which controls an amount of incident light by varying a stop-amount;

a solid-state imaging element, which receives the incident light passed through the diaphragm, ~~and the said~~ solid-state imaging element ~~has~~ having a plurality of pixels, ~~and each of the pixels is being~~ divided into a main pixel, which has a first area ~~and read for~~ obtaining a high-sensitivity image signal, and a sub-pixel, which has a second area which is smaller than the first area, ~~and read for~~ obtaining a low-sensitivity image signal; ~~and~~

a controller, which individually controls a gain amount of the high-sensitivity image signal and a gain amount of the low-sensitivity image signal in response to the stop-amount of the ~~diaphragm, diaphragm;~~ diaphragm; and

a synthesizing processor, which synthesizes the controlled high-sensitivity image signal and the controlled low-sensitivity image signal.

2. (Original) The digital camera according to claim 1,

wherein the controller increases the gain amount of the high-sensitive image signal and decreases the gain amount of the low-sensitive image signal when the diaphragm is set to an open side, whereas the controller decreases the gain amount of the high-sensitive image signal and increases the gain amount of the low-

sensitive image signal when the diaphragm is set to a small-stop side.

3. (Original) The digital camera according to Claim 1,

wherein when the controller increases the gain amount of the low-sensitive image signal, the controller decreases a synthesizing ratio of the low-sensitive image signal synthesized with the high-sensitive image signal.

4. (Currently Amended) The digital camera according to claim 1, wherein the plurality of pixels ~~is~~ are arranged in an array shape.

5. (Currently Amended) The digital camera according to claim 1, wherein each of the pixels is divided into the main pixel and the sub-pixel by an element separating band deviated from a center of the pixel.

6. (Currently Amended) A digital camera comprising:

a diaphragm, which controls an amount of incident light by ~~an~~ a stop-amount;

a solid-state imaging element, which receives the incident light passed through the diaphragm, ~~and the~~ said solid-state imaging element ~~has~~ having a plurality of pixels, ~~and each of the pixels is~~ being divided into

a main pixel, which has a first area ~~and read~~ for obtaining a high-sensitivity image signal, and

a sub-pixel, which has a second area, ~~area~~ which is smaller than the first area, ~~and read~~ for obtaining a low-sensitivity image signal; ~~and~~

a controller, which operates in such a manner the smaller a stop amount of the diaphragm becomes, the smaller a synthesizing ratio of the low-sensitive image signal with respect to the high-sensitive image signal is ~~decreased~~, decreased; and

a synthesizing processor, which synthesizes the high-sensitivity image signal with the low-sensitivity image signal.

7. (Currently Amended) The digital camera according to claim 6, wherein the plurality of pixels ~~is~~ are arranged in an array shape.

8. (Original) The digital camera according to claim 6, each of the pixels is divided into the main pixel and the sub-pixel by an element separating band deviated from a center of the pixel.

9. (New) A method for controlling a digital camera, said method comprising:

varying a stop-amount of a diaphragm to control an amount of incident light;

receiving incident light passed through the diaphragm on a solid-state imaging element, said solid-state imaging element having a plurality of pixels, each of the pixels being divided into a main pixel, which has a first area for obtaining a high-sensitivity image signal, and a sub-pixel, which has a second area

which is smaller than the first area, for obtaining a low-sensitivity image signal;

individually controlling a gain amount of the high-sensitivity image signal and a gain amount of the low-sensitivity image signal in response to the stop-amount of the diaphragm; and

synthesizing the controlled high-sensitivity image signal and the controlled low-sensitivity image signal.

10. (New) The method according to claim 9,

wherein said controlling step increases the gain amount of the high-sensitivity image signal and decreases the gain amount of the low-sensitivity image signal when the diaphragm is set to an open side, and said controlling step decreases the gain amount of the high-sensitivity image signal and increases the gain amount of the low-sensitivity image signal when the diaphragm is set to a small-stop side.

11. (New) The method according to claim 9,

wherein when said controlling step increases the gain amount of the low-sensitivity image signal, the controlling step decreases a synthesizing ratio of the low-sensitivity image signal synthesized with the high-sensitivity image signal.

12. (New) The method according to claim 9, wherein the plurality of pixels are arranged in an array shape.

13. (New) The method according to claim 9, wherein each of the pixels is divided into the main pixel and the sub-pixel by an element separating band deviated from a center of the pixel.

14. (New) A method of controlling a digital camera, said method comprising:

setting a stop-amount of a diaphragm to control an amount of incident light;

receiving the incident light passed through the diaphragm on a solid-state imaging element, said solid-state imaging element having a plurality of pixels, each of the pixels being divided into

a main pixel, which has a first area for obtaining a high-sensitivity image signal, and

a sub-pixel, which has a second area, which is smaller than the first area, for obtaining a low-sensitivity image signal;

controlling a synthesizing ratio of the low-sensitivity signal with respect to the high-sensitivity image signal, such that the smaller a stop amount of the diaphragm becomes, the smaller a synthesizing ratio of the low-sensitivity image signal with respect to the high-sensitivity image signal is decreased; and

synthesizing the high-sensitivity image signal with the low-sensitivity image signal.

15. (New) The method according to claim 14, wherein the plurality of pixels are arranged in an array shape.

16. (New) The method according to claim 14, wherein each of the pixels is divided into the main pixel and the sub-pixel by an element separating band deviated from a center of the pixel.